TV Level Meter

Protek

Protek MM-0090T

Features

MM-0090T is a TV level meter designed for the installation and maintenance of reception and distribution system for analog and digital television signals.

MM-0090T performs all the measurements necessary for ensuring good operation of any installation within the 5 to 900MHz range because of the basic functions for signal analysis provided accurate, economical and easyusing of the device.

It performs the following types of

- For analog channels:
 - Image carrier level;
 - Carrier to Noise (C/N) ratio;
 - Video to Audio (V/A) ratio.
- For Digital channels:
 - Channel power:
 - Carrier to Noise (C/N) ratio.



Specifications

opecilications	
Tuning range	5 to 900MHz
Tuning resolution	125kHz
Level measurement range	30 to 126dBuV
Level measurement resolution	0,1dB
Measurement accuracy	\pm 1,5dB (within temperature range 18 to 28°C) \pm 2,2dB (within temperature range $-$ 10 to 40°C)
Measurement accuracy	6pcs rechargeable, NiMH, AA, 2100mAh
Power supply external	mains adapter 12V/0,8A
Remote control interface	serial interface RS-232
Operating temperature range	−10 to +40°C